

LW 4005 KIT

BASS:	
TREBLE:	Midrange 2x10" LW5001MF+High frequency 1x1,75" LW5201HFM with internal processor
HORN:	70° x 40° for mid-high LW 5101 HFD-MFD with pan/tilt adjustment
POWER:	470W AES, 540W Prg. Nominal impedance 4 ohm
SENSITIVITY:	112dB/1W/1m. Free field SPL 136,3dB
FREQUENCY RESPONSE:	(-10dB) 70/18.000Hz. Use 400Hz. crossover for bi-amp.
SIZE:	101,5 x 66 x 47 cm.
WEIGHT:	29 Kg.



With the digital cinema in mind, this conversion Kit is a plug & play add-on to any kind of 2x15" bass system in good condition, turning it into an improved bi-amplified three way system.

The human voice (mid-range frequency) is perfectly played back by the cone speakers together with the polyester horn. A powerful 1,75" driver delivers clear high frequencies.

